SIEMENS

Data sheet

3RP25 40-1AB30



TIMING RELAY, ELECTRONIC, OFF-DELAY, WITHOUT CONTROL SIGNAL OR NON-VOLATILE RELAY DEFINITE PASSING MAKE CONT., 24 V AC/DC, 1 CO CONTACT 7 TIME SET. RANG. 0.05S...600S, WITH LED, SCREW TERMINAL

Figure similar

General technical data:		
product brand name		SIRIUS
Product designation		timing relay
mounting position		any
Product function at the relay outputs Switchover delayed/without delay		No
Product function non-volatile		Yes
Product component		
Relay output		Yes
 semi-conductor output 		No
Installation altitude at height above sea level maximum	m	2 000
Ambient temperature		
 during operation 	°C	-25 +60
 during storage 	°C	-40 +85
 during transport 	°C	-40 +85
Relative humidity		
 during operation 	%	15 70
EMC emitted interference acc. to IEC 61812-1		EN 61000-6-4(3)
EMI immunity acc. to IEC 61812-1		EN 61000-6-2
Conducted interference BURST acc. to IEC 61000-4- 4		2 kV network connection / 1 kV control connection
Conducted interference conductor-earth SURGE acc. to IEC 61000-4-5		2 KV
Conducted interference conductor-conductor SURGE acc. to IEC 61000-4-5		1 kV

Electrostatic discharge acc. to IEC 61000-4-2		4 kV contact discharge / 8 kV air discharge
Field-bound parasitic coupling acc. to IEC 61000-4-3	-	10 V/m
Surge voltage resistance Rated value	V	4 000
Active power loss total typical	W	2
Reference code acc. to DIN 40719 extended according to IEC 204-2 acc. to IEC 750	_	К
Reference code acc. to DIN EN 81346-2		К
Category acc. to EN 954-1		none
Protection against electrical shock		finger-safe
Protection class IP	_	IP20
Mechanical service life (switching cycles) typical	_	10 000 000
Electrical endurance (switching cycles) at AC-15 at 230 V typical	_	100 000
Operating frequency with 3RT2 contactor maximum	1/h	5 000
Shock resistance acc. to IEC 60068-2-27		11g / 15 ms
Relative repeat accuracy	%	1
Recovery time	ms	250
Minimum ON period	ms	200
Degree of pollution		3
Insulation voltage for overvoltage category III according to IEC 60664 with degree of pollution 3 Rated value	V	300
Relative setting accuracy relating to full-scale value	%	5
Switching Function:		
Switching function		
• ON-delay		No
 ON-delay/instantaneous contact 		No
 passing make contact 		No
 passing make contact/instantaneous contact 		
		No
 OFF delay 		No Yes
 OFF delay flashing asymmetrically starting with interval 		
•		Yes
 flashing asymmetrically starting with interval 		Yes No
 flashing asymmetrically starting with interval flashing asymmetrically starting with pulse flashing symmetrically starting with pulse flashing symmetrically starting with 		Yes No No
 flashing asymmetrically starting with interval flashing asymmetrically starting with pulse flashing symmetrically starting with pulse flashing symmetrically starting with pulse/instantaneous 		Yes No No
 flashing asymmetrically starting with interval flashing asymmetrically starting with pulse flashing symmetrically starting with pulse flashing symmetrically starting with 		Yes No No No
 flashing asymmetrically starting with interval flashing asymmetrically starting with pulse flashing symmetrically starting with pulse flashing symmetrically starting with pulse/instantaneous flashing symmetrically starting with interval flashing symmetrically starting with interval 		Yes No No No
 flashing asymmetrically starting with interval flashing asymmetrically starting with pulse flashing symmetrically starting with pulse flashing symmetrically starting with pulse/instantaneous flashing symmetrically starting with interval flashing symmetrically starting with interval 		Yes No No No No
 flashing asymmetrically starting with interval flashing asymmetrically starting with pulse flashing symmetrically starting with pulse flashing symmetrically starting with pulse/instantaneous flashing symmetrically starting with interval flashing symmetrically starting with interval flashing symmetrically starting with interval starting symmetrically starting with interval 		Yes No No No No
 flashing asymmetrically starting with interval flashing asymmetrically starting with pulse flashing symmetrically starting with pulse flashing symmetrically starting with pulse/instantaneous flashing symmetrically starting with interval flashing symmetrically starting with interval flashing symmetrically starting with interval star-delta circuit with delay time 		Yes No No No No

• OFF delay		No
• pulse-shaping		No
OFF delay/instantaneous		No
 ON-delay/OFF-delay/instantaneous 		No
 passing break contact/instantaneous 		No
 additive ON delay/instantaneous 		No
 ON-delay/OFF-delay 		No
 passing make contact 		No
 passing make contact/instantaneous contact 		No
• pulse delayed		No
 pulse delayed/instantaneous 		No
 pulse-shaping/instantaneous 		No
Switching function of interval relay with control signal		
 retrotriggerable with deactivated control signal/instantaneous contact 		No
 retrotriggerable with activated control signal 		No
 retrotriggerable with activated control signal/instantaneous contact 		No
 retriggerable with deactivated control signal 		No
Control circuit/ Control:		
Adjustable time	S	0.05 600

Adjustable time	S	0.05 600
Type of voltage of the control supply voltage		AC/DC
Control supply voltage frequency 1	Hz	50 60
Operating range factor control supply voltage rated value		
• with AC		
— at 50 Hz		0.85 1.1
— at 60 Hz		0.85 1.1
• for DC		0.85 1.1

Auxiliary circuit:		
Contact reliability of the auxiliary contacts		one incorrect switching operation of 100 million switching operations (17 V, 5 mA)
Material of switching contacts		AgSnO2
Operating current of the auxiliary contacts		
• at AC-15		
— at 24 V	А	3
— at 250 V	А	3
• at DC-13		
— at 24 V	А	1
— at 125 V	А	0.2
— at 250 V	А	0.1

Design of the fuse link for short-circuit protection of the auxiliary switch required		fuse gL/gG: 4 A
Thermal current	А	5
Switching capacity current		
 with inductive load 	А	0.01 3
Number of NC contacts		
 delayed switching 		0
 instantaneous contact 		0
Number of NO contacts		
 delayed switching 		0
 instantaneous contact 		0
Number of CO contacts		
 delayed switching 		1
 instantaneous contact 		0

Mounting type		screw and snap-on mounting onto 35 mm standard
		mounting rail
Width	mm	22.5
Height	mm	100
Depth	mm	90
Spacing required with side-by-side mounting		
• upwards	mm	0
• forwards	mm	0
• at the side	mm	0
Backwards	mm	0
 downwards 	mm	0
Spacing required for grounded parts		
Backwards	mm	0
• at the side	mm	0
• upwards	mm	0
• forwards	mm	0
• downwards	mm	0
Spacing required for live parts		
• downwards	mm	0
Backwards	mm	0
• at the side	mm	0
• forwards	mm	0
• upwards	mm	0

Connections/ Terminals:	
Design of the electrical connection for auxiliary and	screw-type terminals
control current circuit	
Type of connectable conductor cross-section	

	1x (0.5 4.0 mm²), 2x (0.5 2.5 mm²)
	1x (0.5 4 mm²), 2x (0.5 1.5 mm²)
	1x (20 12), 2x (20 14)
	1x (20 12), 2x (20 14)
N∙m	0.6 0.8
	N∙m

Certificates/ approvals:		
General Product	Declaration of	other
Approval	Conformity	
		Environmental Confirmations
FHI		
LIIL	EG-Konf.	

Further information

Information- and Downloadcenter (Catalogs, Brochures,...) http://www.siemens.com/industrial-controls/catalogs


Industry Mall (Online ordering system) http://www.siemens.com/industrymall


Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RP25401AB30

Service&Support (Manuals, Certificates, Characteristics, FAQs,...) http://support.automation.siemens.com/WW/view/en/3RP25401AB30/all

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) http://www.automation.siemens.com/bilddb/index.aspx?attID9=3RP25401AB30&lang=en





last modified:

23.02.2015