



PLUG-IN RELAY 4 CHANGEOVER CONT.,W/O TEST BR.  
230V AC

### General technical details:

#### Supply voltage frequency / for auxiliary and control current circuit / rated value

- minimum
- maximum

Hz 50  
Hz 60

#### type of voltage

AC

#### Control supply voltage

- at 50 Hz / at AC / rated value
  - minimum
  - maximum
- at 60 Hz / at AC / rated value
  - minimum
  - maximum

V 230  
V 230  
V 230  
V 230

#### Number of NC contacts

- for auxiliary contacts

0

#### Number of NO contacts

- for auxiliary contacts

0

#### Number of change-over switches

- for auxiliary contacts

4

#### Operating current / of the auxiliary contacts

- at DC-13

<ul style="list-style-type: none"> <li>• at 24 V</li> <li>• at AC-15</li> <li>• at 230 V</li> </ul>	A	6
<b>Design of the switching function</b>	A	4
<ul style="list-style-type: none"> <li>• guided</li> </ul>		changeover switch
<b>Switching behaviour</b>		No
		monostable

#### Mechanical design:

<b>Design of the electrical connection</b>		screw-type terminals
<b>Design of the relay operating mechanism</b>		poled
<b>Product component / jumper socket</b>		No
<b>Width</b>	mm	22.5
<b>Height</b>	mm	28
<b>Depth</b>	mm	35

#### Certificates/approvals:

General Product Approval

other

[ROSTEST](#)



[Manufacturer](#)

#### Further information:

**Information- and Downloadcenter (Catalogs, Brochures,...)**

<http://www.siemens.com/industrial-controls/catalogs>

**Industry Mall (Online ordering system)**

<http://www.siemens.com/industrial-controls/mall>

**CAX-Online-Generator**

<http://www.siemens.com/cax>

**Service&Support (Manuals, Certificates, Characteristics, FAQs,...)**

<http://support.automation.siemens.com/WW/view/en/LZX:PT520730/all>

**Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)**

[http://www.automation.siemens.com/bilddb/cax\\_en.aspx?mlfb=LZX:PT520730](http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=LZX:PT520730)

**last change:**

Oct 24, 2011