



SIRIUS, COMPACT STARTER,  
REVERSING STARTER 690 V, 24 V AC/DC,  
50 ... 60 HZ, 0.1 ... 0.4 A, IP20,  
MAIN CIRCUIT CONNECTION: SCREW TERMINAL,  
AUXILIARY CIRCUIT CONNECTION: SCREW TERMINAL

### General technical data:

|   |    |   |
|---|----|---|
| <b>Product brand name</b>                                 |    | SIRIUS  |
| <b>product designation</b>                                |    | compact starter                                 |
| <b>Design of the product</b>                              |    | reversing feeder                                |
| <b>Trip class</b>   |    | CLASS 10 and 20 adjustable                      |
| <b>Product function</b>                                   |    |   |
| • control circuit interface to parallel wiring            |    | Yes   |
| • bus-communication                                       |    | No  |
| • short circuit protection                                |    | Yes   |
| • control circuit interface with IO link                  |    | No  |
| <b>Type of assignment</b>                                 |    | continuous operation according to IEC 60947-6-2 |
| <b>Protection class IP</b>                                |    | IP20  |
| <b>Degree of pollution</b>                                |    | 3   |
| <b>Built in orientation / recommended</b>                 |    | vertical, on horizontal standard mounting rail  |
| <b>Installation altitude / at a height over sea level</b> |    |   |
| • maximum   | m  | 2,000   |
| <b>Ambient temperature</b>                                |    |   |
| • during storage  | °C | -55 ... 80                                      |
| • during operating  | °C | -20 ... 60                                      |
| • during transport  | °C | -55 ... 80                                      |

|   |             |  |
|---|-------------|--|
| <b>Relative humidity</b><br>• during operating phase  | %           | 10 ... 90  |
| <b>Resistance against shock</b>   |             | a=60 m/s <sup>2</sup> (6g) with 10 ms per 3 shocks in all axes                   |
| <b>Resistance against vibration</b>   |             | f= 4 ... 5.8 Hz, d= 15 mm; f= 5.8 ... 500 Hz, a= 20 m/s <sup>2</sup> ; 10 cycles |
| <b>Impulse voltage resistance / rated value</b>   | V           | 6,000  |
| <b>Field-bound parasitic coupling</b><br>• according to IEC 61000-4-3   |             | 10 V/m   |
| <b>Insulation voltage / rated value</b>   | V           | 690  |
| <b>Conductor-bound parasitic coupling conductor-earth SURGE</b><br>• according to IEC 61000-4-5   |             | 4 kV main contacts, 2 kV auxiliary contacts                                      |
| <b>Conductor-bound parasitic coupling conductor-conductor SURGE</b><br>• according to IEC 61000-4-5   |             | 2 kV main contacts, 1 kV auxiliary contacts                                      |
| <b>Conductor-bound parasitic coupling BURST</b><br>• according to IEC 61000-4-4   |             | 4 kV main contacts, 2 kV auxiliary contacts                                      |
| <b>Maximum permissible voltage for safe disconnection</b><br>• between main circuit and auxiliary circuit<br>• between control and auxiliary circuit<br>• between auxiliary circuit and auxiliary circuit | V<br>V<br>V | 400<br>300<br>250  |
| <b>Item designation</b><br>• according to DIN 40719 extendable after IEC 204-2 / according to IEC 750<br>• according to DIN EN 61346-2  |             | Q<br>Q   |

#### Main circuit:

|  |                |                      |
|--|----------------|----------------------|
| <b>Operating voltage / at AC-3 / rated value</b><br>• maximum  | V              | 690                  |
| <b>Number of poles / for main current circuit</b>  |                | 3                    |
| <b>Adjustable response current</b><br>• of the current-dependent overload release  | A              | 0.1 ... 0.4          |
| <b>Formula for making capacity limit current</b>   |                | 120 x I <sub>e</sub> |
| <b>Formula for interruption capacity limit current</b>   |                | 100 x I <sub>e</sub> |
| <b>Emitted mechanical power / for 4-pole three-phase motor</b><br>• at 400 V / rated value<br>• at 500 V / rated value<br>• at 690 V / rated value | kW<br>kW<br>kW | 0.09<br>0.12<br>0.18 |
| <b>Service power / at AC-3 / at 400 V / rated value</b>  | W              | 90                   |
| <b>Frequency of operation / at AC-41 / according to IEC 60947-6-2 / maximum</b>  | 1/h            | 750                  |
| <b>Frequency of operation / at AC-43 / according to IEC 60947-6-2 / maximum</b>  | 1/h            | 250                  |

|  |     |            |
|--|-----|------------|
| <b>Off-load operating frequency</b>                  | 1/h | 3,600      |
| <b>Mechanical operating cycles as operating time</b> |     |            |
| • of the main contacts / typical                     |     | 10,000,000 |
| • of the auxiliary contacts / typical                |     | 10,000,000 |
| • of the signal contacts / typical                   |     | 10,000,000 |

#### Control circuit:

|                                   |    |     |
|-----------------------------------|----|-----|
| <b>type of voltage</b>            |    | AC  |
| <b>Control supply voltage / 1</b> |    |     |
| • for DC                          |    |     |
| • rated value                     | V  | 24  |
| • at 50 Hz / for AC               |    |     |
| • rated value                     | V  | 24  |
| • at 60 Hz / for AC               |    |     |
| • rated value                     | V  | 24  |
| <b>Holding power</b>              |    |     |
| • for AC / maximum                | W  | 2.8 |
| • for DC / maximum                | W  | 2.9 |
| <b>Switch-off delay time</b>      | ms | 50  |
| <b>Start-up delay time</b>        | ms | 70  |

#### Auxiliary circuit:

|  |   |         |
|--|---|---------|
| <b>Product extension</b>   |   |         |
| • auxiliary switch   |   | Yes     |
| <b>Number of NC contacts</b>   |   |         |
| • for auxiliary contacts   |   | 0       |
| <b>Number of NO contacts</b>   |   |         |
| • for auxiliary contacts   |   | 2       |
| • of the non-delayed short-circuit release / for alarm contact                                       |   | 1       |
| <b>Number of changeover contacts / of the current-dependent overload release / for alarm contact</b> |   | 1       |
| <b>Operating current / of the auxiliary contacts / at AC-12</b>                                      |   |         |
| • maximum  | A | 10      |
| <b>Electrical switching cycle as operating time / of the auxiliary contacts</b>                      |   |         |
| • at AC-15 / at 6 A / at 230 V / typical   |   | 500,000 |
| • at DC-13 / at 6 A / at 24 V / typical  |   | 100,000 |
| <b>Electrical switching cycle as operating time / of the signal contacts</b>                         |   |         |
| • at AC-15 / at 6 A / at 230 V / typical   |   | 500,000 |
| • at DC-13 / at 6 A / at 24 V / typical  |   | 100,000 |

**Short-circuit:****Design of the fuse link / for short-circuit protection of the auxiliary switch**

- required

fuse gL/gG: 10 A

**Installation/mounting/dimensions:****Type of mounting**

screw and snap-on mounting

**Width**

mm

90

**Height**

mm

170

**Depth**

mm

165

**Built in orientation**

any

**Connections:****Product function**

- removable terminal for main circuit
- removable terminal for auxiliary and control circuit

Yes

Yes

**Design of the electrical connection**

- for main current circuit
- for auxiliary and control current circuit

screw-type terminals

screw-type terminals

**Type of the connectable conductor cross-section**

- for main contacts
  - solid
  - finely stranded
    - with conductor end processing
- for auxiliary contacts
  - solid
  - finely stranded
    - with conductor end processing
- for AWG conductors
  - for main contacts
  - for auxiliary contacts

2x (1.5 ... 6 mm<sup>2</sup>), 1x 10 mm<sup>2</sup>2x (1.5 ... 6 mm<sup>2</sup>)0.5 ... 4 mm<sup>2</sup>, 2x (0.5 ... 2.5 mm<sup>2</sup>)0.5 ... 2.5 mm<sup>2</sup>, 2x (0.5 ... 1.5 mm<sup>2</sup>)

2x (16 ... 10), 1x 8

2x (20 ... 14)

**Certificates/approvals:****Verification of suitability**

IEC / EN 60947-6-2

| General Product Approval | Functional Safety / Safety of Machinery | Test Certificates |
|--------------------------|---|-------------------|
|--------------------------|---|-------------------|



CQC



CSA

[ROSTEST](#)


UL

[other](#)
[Manufacturer](#)

#### Shipping Approval

[other](#)


DNV



PRS



RINA

[Manufacturer](#)
[other](#)

#### UL/CSA ratings:

##### Operating current (FLA) / for three-phase squirrel cage motors

- at 480 V / rated value
- at 600 V / rated value

A

0.4

A

0.4

##### Contact rating designation / for auxiliary contacts / according to UL

contacts 21-22, 13-14, 43-44 Q600 / A600, contacts 77-78 R300 / B300, contacts 95-96-98 R300 / D300

#### Reliability figures:

##### B10 value

3,000,000

##### Proportion of dangerous failures

%

50

##### Proportion of dangerous failures / with low demand rate / according to SN 31920

%

40

##### Protection against electrical shock

finger-safe

##### Failure rate (FIT value) / with low demand rate / according to SN 31920

FIT

100

#### Further information:

##### Information- and Downloadcenter (Catalogs, Brochures,...)

<http://www.siemens.com/industrial-controls/catalogs>

##### Industry Mall (Online ordering system)

<http://www.siemens.com/industrial-controls/mall>

##### Cax online generator:

<http://www.siemens.com/cax>

##### Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

<http://support.automation.siemens.com/VW/view/en/3RA6250-1AB32/all>

##### Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)

[http://www.automation.siemens.com/bilddb/cax\\_en.aspx?mlfb=3RA6250-1AB32](http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3RA6250-1AB32)

last change:

Oct 24, 2011