

QR500-B


Access Control QR Reader



Overview:

The QR500 Reader is a new generation of intelligent access control reader. It has fast scanning speed, high recognition rate, high compatibility, and can be connected to ACT365 Access Control Units

The QR500 is a Wiegand enabled device, simple to install, and is perfect for Visitor Management in hotels, B&Bs, sporting facilities, VIP shopping appointments, health clinic appointments, or delivery services, amongst other applications.



QR500-B

Access Control QR Reader

QR500-B Key Features:



High Scanning Speeds with Fast Recognition Rate

Simple to use Access Control QR Scanner with high scanning speeds and high recognition rates



Multiple Application Scenarios for Visitor Management

QR500 can be used in unmanned hotels, gyms, VIP shopping bookings, or health clinic visits in line with ACT365



Quick and Simple installation

Simple to install and wire directly to ACT365 ACUs. See additional mounting requirements



Touchless Reader

With a recognition distance of greater than 50mm for QR codes, simply open your phone with the QR code displayed and scan at reader



Compatible with ACT365**

QR Codes can be generated for visitors in ACT365 and sent via email to visitors with a validity period.

Important Information:

**** Card Reading Functionality is not supported by Vanderbilt in the QR500.**



Additional Information :

Requirements

- For use with ACT365
- 34-Bit Wiegand format built into ACT365
- QR Codes generated directly in ACT365 Cardholder details

Mounting Requirements/Options

- Standard 86 Mounting Box with 60 to 66 mm mounting holes required
- On wall/in wall or desk mounting with Mounting Box (required)

QR500-B

Access Control QR Reader

Technical Data	
Vanderbilt Material Number	N54504-Z155-A100
Power Supply	DC 12V (±5%),USB 5V
Operating Temperature	-10 ~ 50°C
Operating Environment	Internal only
Operating Humidity	20 ~ 80%
Gross Weight	0.24 kgs
Dimensions (H x W x D mm)	86 X 86 X 50
Reading Distance	QR ≥ 5CM
Communication	Wiegand output
Barcode Reading	QR, Data Matrix, PDF417, GS1 Databar, Code 128/ EAN128, UPC/EAN, Codabar, Code 39/93, etc.
Wiegand Output	34-Bit Wiegand



Ordering Information:

Type	Art. No.	Description	Weight*
QR500-B	N54504-Z155-A100	QR500 - Access Control QR Reader	0.32kg

*Gross weight of the product inclusive of the weight of its accessories and packaging.