

LBB 1957/00 Plena Voice Alarm Keypad



- ► Seven zone selection keys
- ► LED indications for zone selection
- ▶ Up to eight keypads can be connected together

The keypad is an extension to the LBB 1956/00 Plena Voice Alarm Call Station that adds seven additional zone-select keys. It has the same stable metal base as the call station. In addition to tabletop use, the special design allows it to be neatly flush-mounted in desktops.

Functions

Each call station supports six zone selections. Connecting one of these units, adds seven zones or zone groups that can be selected. Up to eight keypads can be added to an LBB 1956/00 call station. LEDs on the keypad indicate the active zones.

Controls and indicators

- Seven zone selection keys
- Seven zone selection LEDs
- Eight DIP switches

Interconnections

- Two RJ45 jacks
- 24 VDC input
- Keypad connector

Certifications and Approvals

Region	Certification	on
Europe	CE	Declaration of Conformity

Safety	acc. to EN 60065
Immunity	acc. to EN 55103-2
Emission	acc. to EN 55103-1

Technical Specifications

Electrical

/DC supplied by LBB 1956/00
mA
: 100 x 235 mm 7 x 3.97 x 9.25 in)
rox. 1 kg
cket coupled with LBB 1956/00 or oth BB 1957/00
rcoal with silver

Environmental

Operating temperature	-10 °C to +45 °C (14 °F to +113 °F)
Storage temperature	-40 °C to +70 °C (-40 °F to +158 °F)
Relative humidity	<95%

Ordering Information

LBB 1957/00 Plena Voice Alarm Keypad

LBB1957/00

an extension to the LBB 1956/00 Plena Voice Alarm Call Station that adds seven additional zone-select keys

Americas:
Bosch Communications Systems
12000 Portland Avenue South
Burnsville, Minnesota 55337, USA
Phone: 41-800-392-3497
Fax: +1-800-955-6831
audiosupport@us.bosch.com
www.boschsecurity.com

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2600
Fax: +65 6571 2690
apr.securitysystems@bosch.com
www.boschsecurity.com