



CO-TX-MDL8

| Transmitter CO-TX-MDL8   |                                           |
|--------------------------|-------------------------------------------|
| <b>Article no.</b>       | T60TX-08STL                               |
| <b>Frequency</b>         | 433 MHz , 1 channels                      |
| <b>Code comb.</b>        | 16.777.216                                |
| <b>Output</b>            | 7 mW (by 50 ohm)                          |
| <b>Buttons</b>           | 8 x 1 -step buttons                       |
| <b>No. of batteries</b>  | 3                                         |
| <b>Battery</b>           | Exchangeable                              |
| <b>Type of batteries</b> | 1.5V AAA                                  |
| <b>Weight</b>            | ~ 120 g / ~ 0.3 lb                        |
| <b>Dimensions</b>        | ~ 66 x 113 x 35 mm / ~ 2.6 x 4.4 x 1.4 in |
| <b>Protection</b>        | IP65                                      |
| <b>Temperature</b>       | -20 to +55 C / -4 to +130 F               |
| <b>On/off switch</b>     | No                                        |

The product picture above is for illustrative purposes only, actual product appearance might be slightly different.