



TRANSFORMER SITAS;
 PHASES:1;
 PN/PN(S6)(KVA):1 /5;
 UPRI(V):500+/-5%;
 USEC(V):230;
 ISEC(A):4,35;
 F(HZ):50...60;
 VECTOR GR./SHIELD WNG.:li0 /0;
 TA/ISOKL:40 /B;
 IP00;
 TYPE OF TERMINALS:SCREW/TAB CONNECTION;
 INSTALLATION:SCREW;
 EN 61558-2-1, -2-2,
 -2-4 >UL/CSA-RECOGNIZED< >CONTROL CIRCUIT
 TRANSFORMER< >ISOLATION TRANSFORMER<

General technical details:

product designation		transformer SITAS
product brand name		SIDAC
Operating apparent output / rated value	V·A	1,000
Efficiency		0.93
Manner of switching for transformers		li0
Verification of suitability		CE / cRUus
Product function		
• temperature surveillance		No
• isolation control		No
• short circuit and overload protection		No
Number of the protective coils		0
Short-term vector power	V·A	5,000
Relative short-circuit voltage	%	2.5

Inputs:

Phase number / of the inputs		1
Input voltage		
• _1 / rated value	V	525
• _2 / rated value	V	500

• _3 / rated value	V	475
Electrical input frequency		
• minimum	Hz	50
• maximum	Hz	60

Outputs:		
Phase number / of the outputs		1
Output voltage		
• _1 / rated value	V	230
Electrical output frequency		
• maximum	Hz	60
• minimum	Hz	50

Ambient conditions:		
Thermal class / according to IEC 60085		B
Ambient temperature / rated value	°C	40
Protection class IP		IP00

Mechanical design:		
Design of the electrical connection		
• secondary side / for main current circuit		screw-type terminals / tab terminals
• at the input / for main current circuit		screw-type terminals / tab terminals
Type of mounting		screws
Construction form of the iron core		EI 150/90
Width	m	0.152
Height	m	0.144
Depth	m	0.132

Certificates/approvals:		
General Product Approval	Shipping Approval	other



[Confirmation](#)

[other](#)

Further information:	
Information- and Downloadcenter (Catalogs, Brochures,...)	
http://www.siemens.com/industrial-controls/catalogs	
Industry Mall (Online ordering system)	
http://www.siemens.com/industrial-controls/mall	
CAX-Online-Generator	
http://www.siemens.com/cax	

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

<http://support.automation.siemens.com/WW/view/en/4AM5742-5FT10-0FA0/all>

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)

http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=4AM5742-5FT10-0FA0

last change:

Dec 5, 2011