



BNC Jack Crimp 50Ω
BNC81EZ-L400
Crimp less centre pin

Egnede kabler:
LMR400, FF400


Vægt: 16.73g



EAN: 5704717001453

JYEBAO
BNC81EZ-L400

Parts	Material	Plating(Micro-inch)
Ferrule	Brass	Tin-Zinc-Copper-Alloy 100 Over Copper 50
Contact Pin	Phosphor Bronze	Gold 3 Over Nickel 50 Over Copper 50
Barrel	Brass	Tin-Zinc-Copper-Alloy 100 Over Copper 50
Insulator	Teflon	
Body	Brass	Tin-Zinc-Copper-Alloy 100 Over Copper 50



CABLE ASSEMBLY INSTRUCTION

BNC81EZ-L400

JYE BAO CO., LTD.
TAIPEI TAIWAN R.O.C




DIAGRAM	ASSEMBLY INSTRUCTION
	Step 1: STRIP AS SHOWN .
SHARPEN	Step 2: SHARPEN CENTER CONDUCTOR TIP. Step 3: SLIDE FERRULE " B " OVER CABLE. NOTE: THE STRIPPED CABLE AND POINTED CENTER CONDUCTOR MUST BE STRAIGHT (180°).
	Step 4: LOOSEN BRAIDING AND SLIDE CONNECTOR " A " IN PLACE.
	Step 5: SLIDE FERRULE " B " TOWARDS THE CONNECTOR " A " AND CRIMP.

This part number complies with RoHS.

Notice: JYEBAO reserves the right to make modifications deemed appropriate.